





CSAT-ZH Self Amalgamating Tape

Description

CSAT-ZH is a flexible EPR based tape with excellent electrical, physical and chemical properties.

CSAT-ZH is a self amalgamating tape that maintains a tight insulation build up, for void free electrical stability and permanent resistance to moisture penetration.

Main Features

- Self amalgamating
- Halogen free
- Outstanding corona, UV, ozone resistance
- Easily applied-no tools or heat required
- Excellent cold weather seal and corrosion protection
- Over 3:1 stretch ratio
- Operating temperature -55°C to 105°C



CONUSP





Technical Data Physical

| Property | Test Method | Typical Performance |
|---------------------|-------------|---------------------|
| Tensile Strength | DEF 59/97-3 | 2.50 MPA |
| Elongation | DEF 59/97-3 | 750% |
| Heat Shock | DEF 59/97-3 | 150°C |
| Water Absorption | DEF 59/97-3 | 0.06% |
| Ozone Resistance | DEF 59/97-3 | Pass (visual) |
| Fluid Resistance | DEF 59/97-3 | Pass |
| UV Resistance | DEF 59/97-3 | Pass |
| Dielectric Strength | DEF 59/97-3 | 30kV/mm |
| Dielectric Constant | ASTM D150 | 2.7 (24h at 23°C) |

Dimensions

| ORDERING REF | WIDTH (mm) |
|--------------|------------|
| CSAT-ZH-19 | 19 |
| CSAT-ZH-25 | 25 |
| CSAT-ZH-38 | 38 |
| CSAT-ZH-51 | 51 |

| Colour: | Black |
|--------------|---------|
| Thickness: | 0.76 mm |
| Roll length: | 9 m |

Recommended Uses

- Compression gland seal
- Insulating and jacketing of cables and terminations up to 65kV
- Cable jacket repairs & restoration
- Stable packing medium for splices
- Installation where flame and heat is prohibited
- Insulating and protecting busbars and fittings



WORLDWIDE WEB: www.canusa-emi.com

All information contained in this leaflet is believed to be reliable. We advise however that customers should separately evaluate the suitability of our products for their particular application. CANUSA-EM, Shaw Industries and DSG-Canusa GmbH & Co. KG give no guarantees in respect of the accuracy or sufficiency of the information presented and disclaim any liability regarding its use. Our responsibilities are only those listed in our Standard Terms and Conditions of Sale for these products. In no instance will we be liable for any eventual, indirect, or consequential damage or damages arising from the sale, resale, transfer, use or misuse of the product.

